## **Data sheet**

6ES7522-1BH10-0AA0



SIMATIC S7-1500, digital output module, DQ16xDC 24V/0.5A BA, 16 channels in groups of 8, 4 A per group; the module supports the safety-oriented shutdown of load groups up to SIL2 according to EN IEC 62061:2021 and Category 3 / PL d according to EN ISO 13849-1:2015. delivery incl. front connector push-in

General information	
Product type designation	DQ 16x24VDC/0.5A BA
HW functional status	From FS01
Firmware version	V1.0.0
FW update possible	Yes
Product function	
● I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
Prioritized startup	Yes
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V13 / V13
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3 / -
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	V1.0 / V5.1
PROFINET from GSD version/GSD revision	V2.3 / -
Operating mode	
• DQ	Yes
<ul> <li>DQ with energy-saving function</li> </ul>	No
• PWM	No
<ul> <li>Oversampling</li> </ul>	No
• MSO	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes; through internal protection with 7 A per group
Input current	
Current consumption, max.	30 mA
output voltage / header	
Rated value (DC)	24 V
Power	
Power available from the backplane bus	1.15 W
Power loss	
Power loss, typ.	2.2 W
Digital outputs	
Type of digital output	Transistor
Number of digital outputs	16
Current-sourcing	Yes
Digital outputs, parameterizable	No
Short-circuit protection	Yes
<ul> <li>Response threshold, typ.</li> </ul>	1 A

Limitation of inductive shutdown voltage to	L+ (-53 V)
Controlling a digital input	Yes
Switching capacity of the outputs	0.5.4
with resistive load, max.	0.5 A
on lamp load, max.  Load resistance range.	5 W
Load resistance range  • lower limit	48 Ω
	4ο Ω
upper limit  Output voltage	12 112
• for signal "1", min.	L+ (-0.8 V)
Output current	E. ( 0.0 v)
• for signal "1" rated value	0.5 A
• for signal "1" permissible range, max.	0.5 A
• for signal "0" residual current, max.	0.5 mA
Output delay with resistive load	
• "0" to "1", max.	100 μs
• "1" to "0", max.	500 μs
Parallel switching of two outputs	
• for logic links	Yes
• for uprating	No
for redundant control of a load	Yes
Switching frequency	
<ul><li>with resistive load, max.</li></ul>	100 Hz
<ul> <li>with inductive load, max.</li> </ul>	0.5 Hz; According to IEC 60947-5-1, DC-13
on lamp load, max.	10 Hz
Total current of the outputs	
<ul> <li>Current per channel, max.</li> </ul>	0.5 A; see additional description in the manual
<ul> <li>Current per group, max.</li> </ul>	4 A; see additional description in the manual
Current per module, max.	8 A; see additional description in the manual
Cable length	
<ul><li>shielded, max.</li></ul>	1 000 m
<ul> <li>unshielded, max.</li> </ul>	600 m
·	660 III
Interrupts/diagnostics/status information	
Interrupts/diagnostics/status information Diagnostics function	No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable	
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms	No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms  • Diagnostic alarm	No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm  • Maintenance interrupt	No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm  • Maintenance interrupt  Diagnoses	No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm  • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage	No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm • Maintenance interrupt  Diagnoses • Monitoring the supply voltage • Wire-break	No No No No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage • Wire-break • Short-circuit	No No No No No No No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm  • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage  • Wire-break  • Short-circuit  • Group error	No No No No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage • Wire-break • Short-circuit	No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm  • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage  • Wire-break  • Short-circuit  • Group error  Diagnostics indication LED	No No No No No No No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage • Wire-break • Short-circuit • Group error  Diagnostics indication LED • RUN LED • ERROR LED	No Yes; green LED Yes; red LED
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED	No Yes; green LED
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  • Diagnostic alarm • Maintenance interrupt  Diagnoses  • Monitoring the supply voltage • Wire-break • Short-circuit • Group error  Diagnostics indication LED  • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED)	No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display	No Yes; green LED Yes; green LED Yes; green LED Yes; green LED
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	No Yes; green LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	No Yes; green LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	No Yes; green LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED  RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics  Potential separation  Potential separation channels	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED  RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics  Potential separation  Potential separation channels between the channels	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics  Potential separation  Potential separation channels between the channels, in groups of	No No No No No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics  between the channels between the channels between the channels and backplane bus	No No No No No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED  RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics  for module diagnostics  between the channels between the channels and backplane bus	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics  for module diagnostics between the channels between the channels between the channels and backplane bus	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information  Diagnostics function  Substitute values connectable  Alarms  Diagnostic alarm Maintenance interrupt  Diagnoses  Monitoring the supply voltage Wire-break Short-circuit Group error  Diagnostics indication LED RUN LED RUN LED RUN LED FRAGR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus	No No No No No No No No No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No

Highest safety class achievable for safety-related tripping of standard modules		
<ul> <li>Performance level according to ISO 13849-1</li> </ul>	PL d	
<ul> <li>Category according to ISO 13849-1</li> </ul>	Cat. 3	
<ul> <li>SIL acc. to IEC 62061</li> </ul>	SIL 2	
<ul> <li>remark on safety-oriented shutdown</li> </ul>	https://support.industry.siemens.com/cs/de/de/view/39198632	
Ambient conditions		
Ambient temperature during operation		
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C; from FS04	
<ul> <li>horizontal installation, max.</li> </ul>	60 °C	
<ul> <li>vertical installation, min.</li> </ul>	-30 °C; from FS04	
vertical installation, max.	40 °C	
Altitude during operation relating to sea level		
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual	
Dimensions		
Width	25 mm	
Height	147 mm	
Depth	129 mm	
Weights		
Weight, approx.	230 g	
Other		
Note:	Supplied incl. 40-pole push-in front connectors	

last modified: